

A classification of techniques for the compensation of time delayed processes. Part 1. Parameter optimised controllers.

AIDAN O'DWYER,
School of Control Systems and Electrical Engineering,
Dublin Institute of Technology,
Kevin St., Dublin 8,
IRELAND.

JOHN RINGWOOD,
School of Electronic Engineering,
Dublin City University, Dublin 9,
IRELAND.

Abstract:- An extensive literature exists on the compensation of time delayed processes. It is possible to identify themes that are common to many of the available techniques. The intention of the two parts of this paper is to provide a framework against which the literature may be viewed; Part 1 of the paper considers the use of parameter optimised controllers for the compensation problem, with Part 2 of the paper considering the use of structurally optimised compensators. Conclusions are drawn at the end of Part 2.

Keywords:- Time delay, compensation, PID, dead-time compensators. *CSCC'99 Proceedings*, Pages:1341-1349

1 Introduction

A time delay may be defined as the time interval between the start of an event at one point in a system and its resulting action at another point in the system. Delays are also known as transport lags or dead times; they arise in physical, chemical, biological and economic systems, as well as in the process of measurement and computation. Methods for the compensation of time delayed processes may be broadly divided into parameter optimised (or PI/PID) controllers, in which the controller parameters are adapted to the controller structure, and structurally optimised controllers, in which the controller structure and parameters are adapted optimally to the structure and parameters of the process model [1, 2]. Other reviews, detailing elements of the topics treated, are recommended to the interested reader [3-13].

2 PI/PID controllers

2.1 Introduction

The PID (proportional integral derivative) controller and its variations (P, PI or PD) is the

most commonly used controller in process control applications, for the compensation of both delayed and non-delayed processes. The PID controller may be implemented in continuous or discrete time, in a number of controller structures [14]. The ideal continuous time PID controller is expressed in Laplace form as follows:

$$G_c(s) = K_c \left(1 + \frac{1}{T_i s} + T_d s \right) \quad (1)$$

with K_c = proportional gain, T_i = integral time constant and T_d = derivative time constant. If $T_i = \infty$ and $T_d = 0$ (i.e. P control), then the closed loop measured value will always be less than the desired value for processes without an integrator term, as a positive error is necessary to keep the measured value constant, and less than the desired value. The introduction of integral action facilitates the achievement of equality between the measured value and the desired value, as a constant error produces an increasing controller output. The introduction of derivative action means that changes in the desired value may be anticipated, and thus an appropriate correction may be added prior to the actual change. Thus, in simplified

terms, the PID controller allows contributions from present, past and future controller inputs.

In many cases, the design of PID controllers for delayed processes are based on methods that were originally used for the controller design of delay-free processes. It has been suggested that there are perhaps 5-10% of control loops that cannot be controlled adequately by PID controllers [3]; in particular, the PID controller performs well if the performance requirements are modest [15, 16]. PID controllers have some robustness to incorrect process model order assumptions [17] and limited process parameter changes. The controller is also easy to understand, with tuning rules that have been validated in a wide variety of practical cases. However, PID controllers are not well suited for the control of dominant delay processes [18, 19]. It has been suggested that the PID implementation is recommended for the control of processes of low to medium order, with small delays, when controller parameter setting must be done using tuning rules and when controller synthesis may be performed a number of times [1].

2.2 The specification of PI or PID controller parameters

2.2.1 Iterative methods

The choice of appropriate compensator parameters may be achieved experimentally e.g. by manual tuning [18, 20-24]. However, such an approach is time consuming and the process typically has to be driven to its stability limit [20]. Alternatively, a graphical or analytical approach to controller tuning may be done in either the time or frequency domain. The time domain design is done using root locus diagrams; it is, however, questionable that a delayed process would be sufficiently well modelled by the necessary second order model. The frequency domain design is typically done using Bode plots [25-29] to achieve a desired phase margin [26, 30]. Similar methods are also described in the discrete time domain [30]. Iterative methods for controller design provide a first approximation to desirable controller parameters.

2.2.2 Tuning rules

Process reaction curve tuning rules are based on calculating the controller parameters from the model parameters determined from the open loop process step response. This method was originally suggested by Ziegler and Nichols [31],

who modelled the single input, single output (SISO) process by a first order lag plus delay (FOLPD) model, estimated the model parameters using a tangent and point method and defined tuning parameters for the P, PI and PID controllers. Other process reaction curve tuning rules of this type are also described, sometimes in graphical form, to control processes modelled by a FOLPD model [16, 32-43] and an integral plus delay (IPD) model [16, 31, 33, 44, 45]. The advantages of such tuning strategies are that only a single experimental test is necessary, a trial and error procedure is not required and the controller settings are easily calculated; however, it is difficult to calculate an accurate and parsimonious process model and load changes may occur during the test which may distort the test results [20]. These methods may also be used to tune cascade compensators [46], discrete time compensators [1, 47] and compensators for delayed multi-input, multi-output (MIMO) processes [48].

Performance (or optimisation) criteria, such as the minimisation of the integral of absolute error in a closed loop environment, may be used to determine a unique set of controller parameter values. Tuning rules have been described, sometimes in graphical form, to optimise the regulator response of a compensated SISO process, modelled in stable FOLPD form [32, 36, 40, 49-57], unstable FOLPD form [53, 58], IPD form [32, 54, 59-61], stable second order system plus delay (SOSPD) form [54, 57, 59, 62-69] and unstable SOSPD form [48, 60, 70]. Similarly, tuning rules have been proposed to optimise the servo response of a compensated process, modelled in stable FOLPD form [40, 51, 52, 56, 57, 71-74], unstable FOLPD form [58], stable SOSPD form [57, 67-69, 71] and unstable SOSPD form [58]. Tuning rules to achieve specified servo and regulator responses simultaneously are also described [75-77]. Cascade controllers [71, 78, 79] and discrete time compensators [1, 80-83] may also be tuned.

Ultimate cycle tuning rules are calculated from the controller gain and oscillation period recorded at the ultimate frequency (i.e. the frequency at which marginal stability of the closed loop control system occurs). The first such tuning methods was defined by Ziegler and Nichols [31] for the tuning of P, PI and PID controller parameters of a process that may or may not include a delay. The tuning rules implicitly build an adequate frequency domain stability margin into the compensated system [84]. Such tuning rules, to compensate delayed processes by minimising a performance criterion, or achieving a specified gain

and/or phase margin are discussed when the SISO process is modelled in FOLPD form [5, 38, 53, 54, 56, 59, 85-93], IPD form [45, 54, 94, 95], first order lag plus integral plus delay (FOLIPD) form [85], stable SOSPD form [53, 54, 86, 96] or unstable SOSPD form [85]. Alternatively, ultimate cycle tuning rules, and modifications of the rules in which the proportional gain is set up to give a closed loop transient response decay ratio of 0.25, or a phase lag of 135° , may compensate general, possibly delayed, processes [16, 19, 27, 39, 42, 44, 88, 97-108], sometimes to achieve a specified gain and/or phase margin [5, 16, 84, 108-114] or a specified closed loop response [115-117]. Ultimate cycle tuning rules may also be used to tune cascade controllers [42, 118], discrete time compensators [1, 20, 119, 120] and compensators for delayed MIMO processes [2, 42, 121-131]. The controller settings are easily calculated; however, the system must generally be destabilised under proportional control, the empirical nature of the method means that uniform performance is not achieved in general [132], several trials must typically be made to determine the ultimate gain, the resulting process upsets may be detrimental to product quality and there is a danger of misinterpreting a limit cycle as representing the stability limit [88].

Direct synthesis tuning rules result in a controller that facilitates a specified closed loop response. These methods include pole placement strategies and frequency domain techniques, such as gain margin and/or phase margin specification. Schneider [133], for example, specified a PI tuning rule to control a FOLPD process model, which results in a closed loop response damping factor of unity. Other such tuning rules also compensate SISO processes modelled in stable FOLPD form [5, 16, 64, 73, 134-145], unstable FOLPD form [146-148], IPD form [16, 141, 143, 144, 149, 150] and SOSPD form [5, 134, 137, 151-155]. Frequency domain based tuning rules are also described, for processes modelled in stable FOLPD form [42, 56, 93, 156-161], unstable FOLPD form [162-165], stable SOSPD form [28, 93, 158, 166-169], unstable SOSPD form [165] and more general form [28, 113, 160, 170-172]. The methods may also be used to tune cascade compensators [142], discrete time compensators [137, 138, 173, 174], and compensators for delayed MIMO processes [175].

The presence of unmodelled process dynamics demands a robust design approach. The Internal Model Control (IMC) design procedure, which allows uncertainty on the process parameters to be specified, may be used to design appropriate PI and PID controllers for the compensation of

SISO processes modelled in stable FOLPD form [176-186], unstable FOLPD form [187], IPD form [178, 185, 186], stable SOSPD form [166, 176, 178, 179, 181, 188] and unstable SOSPD form [187]. Cascade controllers [146, 189, 190] and controllers for delayed MIMO processes [191, 192] may also be tuned using the strategy.

Tuning rules are easy to use, even in the absence of an accurate process model. These design methods are suitable for the achievement of a simple performance specification, for a compensated process with a non-dominant delay. Comprehensive summaries of the tuning rule formulae are available [193, 194].

2.1.3 Analytical techniques

Controller parameters may be determined using analytical techniques. Some methods minimise an appropriate performance index; Harris and Mellichamp [195], for instance, outline a methodology to tune a PI or PID controller to meet multiple closed loop criteria. These criteria are subsumed into a single performance index that is an arbitrary function of relevant frequency domain parameters; the method reflects the important point that there is no one set of tuning values that provide the optimum response in all respects. Other such methods to determine compensators for delayed SISO processes have also been described, both in continuous time [196-212] and discrete time [1, 2, 102, 213-221]. Compensators for delayed MIMO processes have also been proposed in continuous time [222-224] and discrete time [2].

Alternatively, a direct synthesis strategy may be used to determine the controller parameters. Such strategies may be defined in the time domain, possibly by using pole placement [15, 97, 225-236] or in the frequency domain, possibly by specifying a desired gain and/or phase margin [175, 237-254]. Barnes *et al.* [243], for instance, design a PID controller for a delayed process by minimising the sum of squared errors between the desired and actual polar plots. Direct synthesis strategies may also be used in the discrete time domain [1, 255-259].

Robust methods, based on the IMC design procedure, may be used to design analytically an appropriate PID controller for a FOLPD process model both with delay uncertainty and with general parameter uncertainty [182]. Other analytical applications of the IMC procedure are also discussed [260]. Other robust strategies may also be used to design the controllers [261-263]. Finally, alternative design methods may be used to

determine the controller parameters, such as pattern recognition [264, 265], the use of expert systems [266-272], fuzzy logic [8, 230, 273-276], genetic algorithms [277-279] or neural networks [42].

Analytical methods are suitable for the design of PI/PID controllers for non-dominant delay processes where there are well-defined performance requirements to be achieved [1].

References [1-279]:

- [1] Isermann, R., *Digital control systems Volume 1. Fundamentals, deterministic control*, 2nd Revised Edition, Springer-Verlag, 1989.
- [2] Isermann, R., *Digital control systems Volume 2. Stochastic control, multivariable control, adaptive control, applications*, 2nd Revised Edition, Springer-Verlag, 1991.
- [3] Koivo, H.N. and Tanttu, J.T., Tuning of PID controllers: survey of SISO and MIMO techniques, Proceedings of the *IFAC Intelligent Tuning and Adaptive Control Symposium*, 1991, Singapore, pp. 75-80.
- [4] Bueno, S.S., De Keyser, R.M.C. and Favier, G., Auto-tuning and adaptive tuning of PID controllers, *Journal A*, Vol. 32, No. 1, 1991, pp. 28-34.
- [5] Astrom, K.J., Hagglund, T., Hang, C.C. and Ho, W.K., Automatic tuning and adaptation for PID controllers - a survey, *Control Engineering Practice*, Vol. 1, 1993, pp. 699-714.
- [6] Astrom, K.J., Lee, T.H., Tan, K.K. and Johansson, K.H., Recent advances in relay feedback methods - a survey, Proceedings of the *IEEE International Conference on Systems, Man and Cybernetics*, Vol. 3, 1995, pp. 2616-2621.
- [7] Astrom, K.J., Tuning and adaptation, Proceedings of the *13th World Congress of the International Federation of Automatic Control*, San Francisco, CA, USA, Plenary Volume, 1996, pp. 1-18.
- [8] Chen, G., Conventional and fuzzy PID controllers: an overview, *International Journal of Intelligent Control and Systems*, Vol. 1, No. 2, 1996, pp. 235-246.
- [9] Gorez, R., A survey of PID auto-tuning methods, *Journal A*, Vol. 38, 1997, pp. 3-10.
- [10] Marshall, J.E., Chotai, A. and Garland, B., A survey of time-delay system control methods, Proceedings of the *Conference on Control and its Applications*, IEE Conference Publication Number 194, Warwick, U.K., 1981, pp. 316-322.
- [11] Wang, J. and Wan, B.-W., Control approaches for processes with large time delays: a review, *ISA Transactions*, Vol. 27, 1988, pp. 61-65.
- [12] Seborg, D.E., Edgar, T.F. and Shah, S.L., Adaptive control strategies for process control: a survey, *AIChE Journal*, Vol. 32, 1986, pp. 881-913.
- [13] Fisher, D.G., Process control: an overview and personal perspective, *The Canadian Journal of Chemical Engineering*, Vol. 69, 1991, pp. 5-26.
- [14] Astrom, K.J. and Wittenmark, B., *Computer controlled systems: theory and design*, Prentice-Hall International Inc., 1984.
- [15] Hwang, S.-H., Adaptive dominant pole design of PID controllers based on a single closed-loop test, *Chemical Engineering Communications*, Vol. 124, 1993, pp. 131-152.
- [16] Astrom, K.J. and Hagglund, T., *PID controllers: theory, design and tuning*, Second Edition, Instrument Society of America, 1995.
- [17] Lammers, H.C. and Verbruggen, H.B., Simple self-tuning control of processes with a slowly varying time delay, Proceedings of the *IEE Control Conference*, 1985, pp. 393-398.
- [18] Deshpande, P.B. and Ash, R.H., *Elements of computer process control with advanced control applications*, Instrument Society of America, Prentice-Hall Inc., 1983.
- [19] Hagglund, T. and Astrom, K.J., Industrial adaptive controllers based on frequency response techniques, *Automatica*, Vol. 27, 1991, pp. 599-609.
- [20] Seborg, D.E., Edgar, T.F. and Mellichamp, D.A., *Process dynamics and control*, John Wiley and Sons, 1989.
- [21] Pollard, A., *Process control*, Heinemann Educational Books, 1971.
- [22] Power, H.M. and Simpson, R.J., *Introduction to dynamics and control*, McGraw-Hill, 1978.
- [23] Leigh, J.R., *Applied control theory*, Revised 2nd edition, Peter Peregrinus Ltd., 1987.
- [24] Lee, J., Cho, W. and Edgar, T.F., Multiloop PI controller tuning for interacting multivariable processes, *Computers and Chemical Engineering*, Vol. 22, No. 11, pp. 1711-1723.
- [25] Kuo, B.C., *Automatic control systems*, 6th Edition, Prentice-Hall Inc., 1991.
- [26] Phillips, C.L. and Harbor, R.D., *Feedback control systems*, 2nd edition, Prentice-Hall, 1991.
- [27] Atkinson, P. and Davey, R.L., A theoretical approach to the tuning of pneumatic three-term controllers, *Control*, March, 1968, pp. 238-242.
- [28] Hougen, J.O., *Measurement and control applications*, Instrument Society of America, 1979.
- [29] Hougen, J.O., A software program for process controller parameter selection, Proceedings of the *ISA/88 International Conference and Exhibition. Advances in Instrumentation*, Vol. 43(1), 1988, pp. 441-456.
- [30] Shahian, B. and Hassul, M., *Control system design using MATLAB*, Prentice-Hall, 1993.
- [31] Ziegler, J.G. and Nichols, N.B., Optimum settings for automatic controllers, *Transactions of the ASME*, Vol. 64, 1942, pp. 759-768.
- [32] Hazebroek, P. and Van der Waerden, B.L., The optimum tuning of regulators, *Transactions of the ASME*, April, 1950, pp. 317-322.
- [33] Wolfe, W.A., Controller settings for optimum control, *Transactions of the ASME*, May, 1951, pp. 413-418.
- [34] Chien, K.L., Hrones, J.A. and Reswick, J.B., On the automatic control of generalised passive systems, *Transactions of the ASME*, February, 1952, pp. 175-185.
- [35] Cohen, G.H. and Coon, G.A., Theoretical considerations of retarded control, *Transactions of the ASME*, July, 1953, pp. 827-834.
- [36] Murrill, P.W., *Automatic control of processes*, International Textbook Co., 1967.
- [37] Murrill, P.W. and Smith, C.L., Controllers: set them right, *Hydrocarbon Processing*, Vol. 45, No. 2, 1966, pp. 105-124.
- [38] Astrom, K.J. and Hagglund, T., *Automatic tuning of PID Controllers*, Instrument Society of America, 1988.
- [39] Parr, E.A., *Industrial Control Handbook: Volume 3*, BSP Professional Books, 1989.
- [40] Witt, S.D. and Waggoner, R.C., Tuning parameters for non-PID three-mode controllers, *Hydrocarbon Processing*, June, 1990, pp. 74-78.
- [41] Sain, S.G. and Ozgen, C., Identification and tuning of processes with large deadtime, *Control and Computers*, Vol. 20, No. 3, 1992, pp. 73-78.
- [42] Hang, C.C., Lee, T.H. and Ho, W.K., *Adaptive Control*, Instrument Society of America, 1993.
- [43] McMillan, G.K., *Tuning and control loop performance - a practitioner's guide*, 3rd Edition, Instrument Society of America, 1994.
- [44] Ford, R.L., The determination of the optimum process-controller settings and their confirmation by means of an electronic simulator, *Proceedings of the IEE, Part 2*, Vol. 101, No. 80, April, 1953, pp. 141-155 and pp. 173-177.
- [45] Tyreus, B.D. and Luyben, W.L., Tuning PI controllers for integrator/dead time processes, *Industrial Engineering Chemistry Research*, Vol. 31, 1992, pp. 2625-2628.
- [46] Krishnaswamy, P.R. and Rangaiah, G.P., Role of secondary integral action in cascade control, *Transactions of the Institute of Chemical Engineering*, Vol. 70, Part A, 1992, pp. 149-152.
- [47] Su, L.-S., Applications of digital controller in process control, Proceedings of the *ISA/93 Advances in Instrumentation and Control Conference*, Chicago, U.S.A., 1993, pp. 625-632.
- [48] Jussila, T.T. and Koivo, H.N., Tuning of multivariable PI controllers for unknown delay-differential systems, *IEEE Transactions on Automatic Control*, Vol. AC-32, 1987, pp. 364-368.
- [49] Lopez, A.M., Millar, J.A., Smith, C.L. and Murrill, P.W., Tuning controllers with error-integral criteria, *Instrumentation Technology*, November, 1967, pp. 57-62.
- [50] Miller, J.A., Lopez, A.M., Smith, C.L. and Murrill, P.W., A comparison of controller tuning techniques, *Control Engineering*, December, 1967, pp. 72-75.
- [51] Cheng, G.S. and Hung, J.C., A least-squares based self-tuning of PID controller, Proceedings of the *IEEE South East Conference*, Raleigh, North Carolina, U.S.A., 1985, pp. 325-332.

- [52] Kaya, A. and Scheib, T.J., Tuning of PID controls of different structures, *Control Engineering*, July, 1988, pp. 62-65.
- [53] Shinsky, F.G., *Process control systems - application, design and tuning*, 3rd Edition, McGraw-Hill Inc., 1988.
- [54] Shinsky, F.G., *Process control systems - application, design and tuning*, 4th Edition, McGraw-Hill Inc., 1996.
- [55] Hill, A.G. and Venable, S.W., The effect of model error on optimum PID controller tuning, *Proceedings of the ISA/89 International Conference and Exhibition*, Philadelphia, Pa., U.S.A., Vol. 1, 1989, pp. 51-64.
- [56] Zhuang, M. and Atherton, D.P., Automatic tuning of optimum PID controllers, *IEE Proceedings, Part D*, Vol. 140, 1993, pp. 216-224.
- [57] Huang, C.-T., Chou, C.-J. and Wang, J.-L., Tuning of PID controllers based on the second order model by calculation, *Journal of the Chinese Institute of Chemical Engineers*, Vol. 27, No. 2, 1996, pp. 107-120.
- [58] Huang, C.-T. and Lin, Y.-S., Tuning PID controller for open-loop unstable processes with time delay, *Chemical Engineering Communications*, Vol. 133, 1995, pp. 11-30.
- [59] Shinsky, F.G., *Feedback controllers for the process industries*, McGraw-Hill Inc., 1994.
- [60] Poulin, E. and Pomerleau, A., PID tuning for integrating and unstable processes, *IEE Proceedings - Control Theory and Applications*, Vol. 143, 1996, pp. 429-435.
- [61] Srividya, R. and Chidambaram, M., On-line controllers tuning for integrator plus delay systems, *Process Control and Quality*, Vol. 9, 1997, pp. 59-66.
- [62] Wills, D.M., Tuning maps for three-mode controllers, *Control Engineering*, April, 1962, pp. 104-108.
- [63] Wills, D.M., A guide to controller tuning, *Control Engineering*, August, 1962, pp. 93-95.
- [64] Haalman, A., Adjusting controllers for a deadtime process, *Control Engineering*, July, 1965, pp. 71-73.
- [65] McAvoy, T.J. and Johnson, E.F., Quality of control problem for dead-time plants, *Industrial and Engineering Chemistry Process Design and Development*, Vol. 6, 1967, pp. 440-446.
- [66] Lopez, A.M., Smith, C.L. and Murrill, P.W., An advanced tuning method, *British Chemical Engineering*, Vol. 14, 1969, pp. 1553-1555.
- [67] Sung, S.W., O., J., Lee, I.-B., Lee, J. and Yi, S.-H., Automatic tuning of PID controller using second-order plus time delay model, *Journal of Chemical Engineering of Japan*, Vol. 29, 1996, pp. 990-999.
- [68] Sung, S.W. and Lee, I.-B., Limitations and countermeasures of PID controllers, *Industrial Engineering Chemistry Research*, Vol. 35, 1996, pp. 2596-2610.
- [69] Park, H.I., Sung, S.W., Lee, I.-B. and Lee, J., A simple autotuning method using proportional controller, *Chemical Engineering Communications*, Vol. 161, 1997, pp. 163-184.
- [70] Poulin, E. and Pomerleau, A., Unified PID design method based on a maximum peak resonance specification, *IEE Proceedings - Control Theory and Applications*, Vol. 144, 1997, pp. 566-574.
- [71] Wang, F.-S., Juang, W.-S. and Chan, C.-T., Optimal tuning of PID controllers for single and cascade control loops, *Chemical Engineering Communications*, Vol. 132, 1995, pp. 15-34.
- [72] Rovira, A.A., Murrill, P.W. and Smith, C.L., Tuning controllers for setpoint changes, *Instruments and Control Systems*, December, 1969, pp. 67-69.
- [73] Khan, B.Z. and Lehman, B., Setpoint PI controllers for systems with large normalised dead time, *IEEE Transactions on Control Systems Technology*, Vol. 4, 1996, pp. 459-466.
- [74] Johnson, M.A. and Abdelali, A.S., Process control PID design rules: methods for a comparative study of recent developments, *Proceedings of the IChemE Conference: Advances in Process Control 5*, University of Wales, Swansea, 1998, pp. 121-130.
- [75] Fertik, H.A., Tuning controllers for noisy processes, *ISA Transactions*, Vol. 14, 1975, pp. 292-304.
- [76] Polonyi, M.J.G., PID controller tuning using standard form optimisation, *Control Engineering*, March, 1989, pp. 102-106.
- [77] Seem, J.E., A new pattern recognition adaptive controller with application to HVAC systems, *Automatica*, Vol. 34, No. 8, 1998, pp. 969-982.
- [78] Krishnaswamy, P.R., Rangaiah, G.P., Jha, R.K. and Deshpande, P.B., When to use cascade control, *Industrial Engineering Chemistry Research*, Vol. 29, 1990, pp. 2163-2166.
- [79] Wang, F.-S., Juang, W.-S. and Chan, C.-T., Optimal tuning of cascade PID control systems, *Proceedings of the Second IEEE Conference on Control Applications*, Vancouver, B.C., Canada, 1993, pp. 825-828.
- [80] Moore, C.F., Smith, C.L. and Murrill, P.W., Simplifying digital control dynamics for controller tuning and hardware lag effects, *Instrument Practice*, January, 1969, pp. 45-49.
- [81] Rovira, A.A., Murrill, P.W. and Smith, C.L., Modified PI algorithm for digital control, *Instruments and Control Systems*, August, 1970, pp. 101-102.
- [82] Huang, H.-P. and Chao, Y.-C., Optimal tuning of a practical digital PID controller, *Chemical Engineering Communications*, Vol. 18, 1982, pp. 51-61.
- [83] Shigemasa, T. and Akizuki, K., A closed loop auto-tuning method for digital PID controller, *Proceedings of the IEEE/IECI Conference on applications of mini and microcomputers*, San Francisco, California, U.S.A., 1981, 427-432.
- [84] De Paor, A.M., A fiftieth anniversary celebration of the Ziegler-Nichols PID controller, *International Journal of Electrical Engineering Education*, Vol. 30, 1993, pp. 303-316.
- [85] McMillan, G.K., Control loop performance, *Proceedings of the ISA/84 International Conference and Exhibition. Advances in Instrumentation*, Houston, Texas, Vol. 39(1), 1984, pp. 589-603.
- [86] Hwang, S.-H., Closed-loop automatic tuning of single-input-single-output systems, *Industrial Engineering Chemistry Research*, Vol. 34, 1995, pp. 2406-2417.
- [87] Hwang, S.-H. and Fang, S.-M., Closed-loop tuning method based on dominant pole placement, *Chemical Engineering Communications*, Vol. 136, 1995, pp. 45-66.
- [88] Pessen, D.W., A new look at PID-controller tuning, *Transactions of the ASME. Journal of Dynamic Systems, Measurement and Control*, Vol. 116, 1994, 553-557.
- [89] Hang, C.C. and Astrom, K.J., Refinements of the Ziegler-Nichols tuning formulae for PID auto-tuners, *Proceedings of the ISA/88 International Conference and Exhibition. Advances in Instrumentation*, Vol. 43(3), 1988, pp. 1021-1030.
- [90] Hang, C.C., Astrom, K.J. and Ho, W.K., Refinements of the Ziegler-Nichols tuning formula, *IEE Proceedings, Part D*, Vol. 138, 1991, pp. 111-118.
- [91] Hang, C.-C. and Cao, L., Improvement of transient response by means of variable set-point weighting, *IEEE Transactions on Industrial Electronics*, Vol. 43, 1996, pp. 477-484.
- [92] Astrom, K.J. and Hagglund, T., Automatic tuning of simple regulators with specifications on phase and amplitude margins, *Automatica*, Vol. 20, 1984, pp. 645-651.
- [93] Tan, K.K., Lee, T.H. and Wang, Q.G., Enhanced automatic tuning procedure for process control of PI/PID controller, *AIChE Journal*, Vol. 42, 1996, pp. 2555-2562.
- [94] Luyben, W.L., Tuning proportional-integral-derivative controllers for integrator/deadtime processes, *Industrial Engineering Chemistry Research*, Vol. 35, 1996, pp. 3480-3483.
- [95] Belanger, P.W. and Luyben, W.L., Design of low-frequency compensators for improvement of plantwide regulatory performances, *Industrial Engineering Chemistry Research*, Vol. 36, 1997, pp. 5339-5347.
- [96] Landau, I.D. and Voda, A., An analytical method for the auto-calibration of PID controllers, *Proceedings of the 31st Conference on Decision and Control*, Tucson, Arizona, U.S.A., 1992, pp. 3237-3242.
- [97] Hwang, S.-H. and Chang, H.-C., A theoretical examination of closed-loop properties and tuning methods of single-loop PI controllers, *Chemical Engineering Science*, Vol. 42, 1987, pp. 2395-2415.
- [98] Boe, E., Hwang, S.-W. and Chang, H.-C., Controller tuning based on cross-over information, *Journal of the Chinese Institute of Chemical Engineers*, Vol. 19, 1988, pp. 359-369.
- [99] Blickley, G.J., Modern control started with Ziegler-Nichols tuning, *Control Engineering*, 2 October, 1990, pp. 11-17.
- [100] Corripio, A.B., *Tuning of industrial control systems*, Instrument Society of America, 1990.
- [101] Perry, R.H. and Chilton, C.H., *Chemical engineers handbook*, 5th edition, McGraw-Hill, 1973.
- [102] Karaboga, D. and Kalinli, A., Tuning PID controller parameters using Tabu search algorithm, *Proceedings of the IEEE International Conference on Systems, Man and Cybernetics*, Vol. 1, 1996, pp. 134-136.
- [103] Fu, M., Olbrot, A.W. and Polis, M.P., Comments on "Optimal gain for proportional-integral-derivative feedback", *IEEE Control Systems Magazine*, January, 1989, pp. 100-101.

- [104] Pessen, D.W., Optimum three-mode controller settings for automatic start-up, *Transactions of the ASME*, July, 1953, pp. 843-849.
- [105] Pessen, D.W., How to "tune in" a three-mode controller, *Instrumentation*, Vol. 7, No. 3, 1954, pp. 29-32.
- [106] Grabbe, E.M., Ramo, S. and Woolridge, D.E. (Editors), *Handbook of automation, computation and control. Vol. 3: Systems and Components*, John Wiley and Sons, 1961.
- [107] Harriott, P., *Process control*, McGraw-Hill, New York, U.S.A., 1964.
- [108] Mantz, R.J. and Tacconi, E.J., Complementary rules to Ziegler and Nichols' rules for a regulating and tracking controller, *International Journal of Control*, Vol. 49, 1989, pp. 1465-1471.
- [109] Hang, C.C. and Astrom, K.J., Practical aspects of PID auto-tuners based on relay feedback, Proceedings of the *IFAC Adaptive control of Chemical Processes Conference*, Copenhagen, Denmark, 1988, pp. 153-158.
- [110] Calcev, G. and Gorez, R., Iterative techniques for PID controller tuning, Proceedings of the *34th Conference on Decision and Control*, New Orleans, LA., U.S.A., 1995, pp. 3209-3210.
- [111] Astrom, K.J., *Ziegler-Nichols auto-tuner*, Report TRFT-3167, Department of Automatic Control, Lund Institute of Technology, Lund, Sweden, 1982.
- [112] Vrancic, D., Peng, Y., Strmcnik, S. and Hanus, R., A new tuning method for PI controllers based on a process step response, Proceedings of the *CESA '96 IMACS Multiconference Symposium on Control, Optimisation and Supervision*, Lille, France, Vol. 2, 1996, pp. 790-794.
- [113] Leva, A., PID autotuning algorithm based on relay feedback, *IEE Proceedings, Part D*, Vol. 140, 1993, pp. 328-338.
- [114] Cox, C.S., Arden, W.J.B. and Doonan, A.F., CAD Software facilitates tuning of traditional and predictive control strategies, Proceedings of the *ISA/94 International Conference, Exhibition and Training Program. Advances in Instrumentation and Control*, Anaheim, CA., U.S.A., Vol. 49(2), 1994, pp. 241-250.
- [115] Shin, C.-H., Yoon, M.-H. and Park, I.-S., Automatic tuning algorithm of the PID controller using two Nyquist points identification, Proceedings of the *Society of Instrument and Control Engineers annual conference*, Tokyo, Japan, 1997, pp. 1225-1228.
- [116] Vrancic, D., *Design of anti-windup and bumpless transfer protection. Part II: PID controller tuning by multiple integration method*, PhD thesis, University of Ljubljana, J. Stefan Institute, Ljubljana, Slovenia, 1996.
- [117] Oubrahim, R. and Leonard, F., PID tuning by a composed structure, Proceedings of the *UKACC International Conference on Control '98*, Swansea, Wales, Vol. 2, 1998, pp. 1333-1338.
- [118] Hang, C.C., Loh, A.P. and Vasnani, V.U., Relay feedback auto-tuning of cascade controllers, *IEEE Transactions on Control Systems Technology*, Vol. 2, 1994, pp. 42-45.
- [119] Kofahl, R. and Isermann, R., A simple method for automatic tuning of PID-controllers based on process parameter estimation, Proceedings of the *American Control Conference*, Boston, MA., U.S.A., 1985, pp. 1143-1148.
- [120] Bobal, V., Self tuning Ziegler-Nichols PID controller, *International Journal of Adaptive Control and Signal Processing*, Vol. 9, 1995, pp. 213-226.
- [121] Luyben, W.L., Simple method for tuning SISO controllers in multivariable systems, *Industrial and Engineering Chemistry Process Design and Development*, Vol. 25, 1986, pp. 654-660.
- [122] Loh, A.P. and Vasnani, V.U., Multiloop controller design for multivariable plants, Proceedings of the *31st Conference on Decision and Control*, Tucson, Arizona, U.S.A., 1992, pp. 181-182.
- [123] Loh, A.P., Hang, C.C., Quek, C.K. and Vasnani, V.U., Autotuning of multiloop proportional-integral controllers using relay feedback, *Industrial and Engineering Chemistry Research*, Vol. 32, 1993, pp. 1102-1107.
- [124] Shen, S.-H. and Yu, C.-C., Use of relay-feedback test for automatic tuning of multivariable systems, *AIChE Journal*, Vol. 40, 1990, pp. 627-646.
- [125] Wu, W.-T., Tseng, C.-G. and Chu, Y.T., System identification and on-line robust control of a multivariable system, *International Journal of System Science*, Vol. 25, 1994, pp. 423-439.
- [126] Zhuang, M. and Atherton, D.P., PID controller design for a TITO system, *IEE Proceedings - Control Theory and Applications*, Vol. 141, 1994, pp. 111-120.
- [127] Palmor, Z.J., Halevi, Y. and Krasney, N., Automatic tuning of decentralised PID controllers for TITO processes, *Automatica*, Vol. 31, 1995, pp. 1001-1010.
- [128] Halevi, Y., Palmor, Z.J. and Efrati, E., Automatic tuning of decentralized PID controllers for MIMO processes, *Journal of Process Control*, Vol. 7, 1997, pp. 119-128.
- [129] Semino, D., Mazzanti, I. and Scali, C., Design of decentralized controllers by a relay technique: extension of tuning rules, Proceedings of the *UKACC International Conference on Control*, 1996, pp. 1190-1195.
- [130] Semino, D. and Scali, C., Multiloop autotuning using relay feedback: limits and extensions, Proceedings of the *European Symposium on Computer Aided Process Engineering - 6*, Part B, 1996, pp. S907-S912.
- [131] Wang, Q.-G., Lee, T.-H. and Zhang, Y., Multiloop version of the modified Ziegler-Nichols method for two input, two output processes, *Industrial Engineering Chemistry Research*, Vol. 37, 1998, pp. 4725-4733.
- [132] Hwang, S.-H. and Tseng, T.-S., Process identification and control based on dominant pole expansions, *Chemical Engineering Science*, Vol. 49, 1994, pp. 1973-1983.
- [133] Schneider, D.M., Control of processes with time delays, *IEEE Transactions on Industry Applications*, Vol. 24, 1988, pp. 186-191.
- [134] Pemberton, T.J., PID: The logical control algorithm, *Control Engineering*, Vol. 19, No. 5, 1972, pp. 66-67.
- [135] Smith, C.A. and Corripio, A.B., *Principles and practice of automatic process control*, John Wiley and Sons, 1985.
- [136] Gorecki, H., Fuska, S., Grabowski, P. and Korytowski, A., *Analysis and synthesis of time delay systems*, John Wiley and Sons, 1989.
- [137] Chiu, K.C., Corripio, A.B. and Smith, C.L., Digital controller algorithms. Part III. Tuning PI and PID controllers, *Instruments and Control Systems*, December, 1973, pp. 41-43.
- [138] Suyama, K., A simple design method for sampled-data PID control systems with adequate step responses, Proceedings of the *International Conference on Industrial Electronics, Control, Instrumentation and Automation*, 1992, pp. 1117-1122.
- [139] McAnany, D.E., A pole placement technique for optimum PID control parameters, Proceedings of the *ISA/93 Advances in Instrumentation and Control Conference*, Chicago, Illinois, U.S.A., 1993, pp. 1775-1782.
- [140] Cox, C.S., Daniel, P.R. and Lowden, A., Quicktune: a reliable automatic strategy for determining PI and PPI controller parameters using a FOLPD model, *Control Engineering Practice*, Vol. 5, 1997, pp. 1463-1472.
- [141] Cluett, W.R. and Wang, L., New tuning rules for PID control, *Pulp and Paper Canada*, Vol. 98(6), 1997, pp. 52-55.
- [142] Juang, W.-S. and Wang, F.-S., Design of PID controller by concept of Dahlin's Law, *Journal of the Chinese Institute of Chemical Engineers*, Vol. 26, 1995, pp. 133-136.
- [143] Tsang, K.M., Rad, A.B. and To, F.W., Online tuning of PID controllers using delayed state variable filters, Proceedings of the *IEEE Region 10 Conference on Computer, Communication, Control and Power Engineering*, Vol. 4, 1993, pp. 415-419.
- [144] Tsang, K.M. and Rad, A. B., A new approach to auto-tuning of PID controllers, *International Journal of Systems Science*, Vol. 26, 1995, pp. 639-658.
- [145] Abbas, A., A new set of controller tuning relations, *ISA Transactions*, Vol. 36, 1997, pp. 183-187.
- [146] Jacob, E.F. and Chidambaram, M., Design of controllers for unstable first-order plus time delay systems, *Computers in Chemical Engineering*, Vol. 20, 1996, pp. 579-584.
- [147] Valentine, C.C. and Chidambaram, M., PID control of unstable time delay systems, *Chemical Engineering Communications*, Vol. 162, 1997, pp. 63-74.
- [148] Huang, H.-P. and Chen, C.-C., Control-system synthesis for open-loop unstable process with time delay, *IEE Proceedings - Control Theory and Applications*, Vol. 144, 1997, pp. 334-346.
- [149] Wang, L. and Cluett, W.R., Tuning PID controllers for integrating processes, *IEE Proceedings - Control Theory and Applications*, Vol. 144, 1997, pp. 385-392.
- [150] Penner, A., Tuning rules for a PI controller, Proceedings of the *ISA/88 International Conference and Exhibition: Advances in Instrumentation*, Houston, Texas, U.S.A., Vol. 43(3), 1988, pp. 1037-1051.
- [151] Pemberton, T.J., PID: The logical control algorithm II, *Control Engineering*, Vol. 19, No. 7, 1972, pp. 61-63.

- [152] Smith, C.L., Corripio, A.B. and Martin, J., Controller tuning from simple process models, *Instrumentation Technology*, December, 1975, pp. 39-44.
- [153] Wang, T.-S. and Clements, W.C., Adaptive multivariable PID control of a distillation column with unknown and varying dead time, *Chemical Engineering Communications*, Vol. 132, 1995, pp. 1-13.
- [154] Martin, J., Corripio, A.B. and Smith, C.L., How to select controller modes and tuning parameters from simple process models, *ISA Transactions*, Vol. 15, 1976, pp. 314-319.
- [155] Hang, C.C., Tan, K.K. and Ong, S.L., A comparative study of controller tuning formulae, Proceedings of the *ISA/79 Conference and Exhibition. Advances in Instrumentation*, Chicago, IL., U.S.A., Vol. 34(2), 1979, pp. 467-476.
- [156] Ho, W.K., Hang, C.C. and Zhou, J.H., Performance and gain and phase margins of well-known PI tuning formulas, *IEEE Transactions on Control Systems Technology*, Vol. 3, 1995, pp. 245-248.
- [157] Voda, A. and Landau, I.D., The autocalibration of PI controllers based on two frequency measurements, *International Journal of Adaptive Control and Signal Processing*, Vol. 9, 1995, pp. 395-421.
- [158] Leva, A., Maffezzoni, C. and Scattolini, R., Self-tuning PI-PID regulators for stable systems with varying delay, *Automatica*, Vol. 30, 1994, pp. 1171-1183.
- [159] Li, Z., Su, X. and Lin, P., A practical algorithm for PID auto-tuning, *Advances in Modelling and Analysis C*, ASME Press, Vol. 40, No. 2, 1994, pp. 17-27.
- [160] Friman, M. and Waller, K.V., A two channel relay for autotuning, *Industrial Engineering Chemistry Research*, Vol. 36, 1997, pp. 2662-2671.
- [161] Ho, W.K., Lim, K.W. and Xu, W., Optimal gain and phase margin tuning for PID controllers, *Automatica*, Vol. 34, No. 8, 1998, pp. 1009-1014.
- [162] De Paor, A.M. and O' Malley, M., Controllers of Ziegler-Nichols type for unstable processes with time delay, *International Journal of Control*, Vol. 49, 1989, pp. 1273-1284.
- [163] Venkatasankar, V. and Chidambaram, M., Design of P and PI controllers for unstable first order plus time delay systems, *International Journal of Control*, Vol. 60, 1994, pp. 137-144.
- [164] Chidambaram, M., Design of PI and PID controllers for an unstable first-order plus time delay system, *Hungarian Journal of Industrial Chemistry*, Vol. 23, 1995, pp. 123-127.
- [165] Ho, W.K. and Xu, W., PID tuning for unstable processes based on gain and phase-margin specifications, *IEE Proceedings - Control Theory and Applications*, Vol. 145, No. 5, 1998, pp. 392-396.
- [166] Hang, C.C., Ho, W.K. and Cao, L.S., A comparison of two design methods for PID controllers, Proceedings of the *ISA/93 Advances in Instrumentation and Control Conference*, Chicago, Illinois, U.S.A., 1993, pp. 959-967.
- [167] Ho, W.K., Hang, C.C. and Cao, L.S., Tuning of PID controllers based on gain and phase margin specifications, *Automatica*, Vol. 31, 1995, pp. 497-502.
- [168] Ho, W.K., Hang, C.C. and Zhou, J., Self-tuning PID control of a plant with under-damped response with specifications on gain and phase margins, *IEEE Transactions on Control Systems Technology*, Vol. 5, 1997, pp. 446-452.
- [169] Ho, W.K., Hang, C.C., Zhou, J.H. and Yip, C.K., Adaptive PID control of a process with underdamped response, Proceedings of the *Asian Control Conference*, Tokyo, Japan, 1994, pp. 335-338.
- [170] Zhang, G., Shao, C. and Chai, T., A new method for independently tuning PID parameters, Proceedings of the *35th Conference on Decision and Control*, Kobe, Japan, 1996, pp. 2527-2532.
- [171] Skoczowski, S. and Tarasiejski, L., Tuning of PID controllers based on gain and phase margin specifications using Strejc's process model with time delay, Proceedings of the *Third International Symposium on Methods and Models in Automation and Robotics (MMAR '96)*, Miedzydroje, Poland, 1996, pp. 765-770.
- [172] Lennartson, B. and Kristiansson, B., Pass band and high frequency robustness for PID control, Proceedings of the *36th IEEE Conference on Decision and Control*, San Diego, California, U.S.A., 1997, pp. 2666-2671.
- [173] Keviczky, L. and Banyasz, Cs., A completely adaptive PID regulator, Proceedings of the *IFAC Identification and System Parameter Estimation Conference*, Beijing, China, 1988, pp. 89-95.
- [174] Keviczky, L. and Banyasz, Cs., An adaptive PID regulator based on time delay estimation, Proceedings of the *31st conference on Decision and Control*, Tucson, Arizona, U.S.A., 1992, pp. 3243-3248.
- [175] Ho, W.K., Lee, T.H. and Gan, O.P., Tuning of multiloop proportional-integral-derivative controllers based on gain and phase margin specifications, *Industrial Engineering Chemistry Research*, Vol. 36, 1997, pp. 2231-2238.
- [176] Brambilla, A., Chen, S. and Scali, C., Robust tuning of conventional controllers, *Hydrocarbon Processing*, November, 1990, pp. 53-58.
- [177] Rivera, D.E., Morari, M. and Skogestad, S., Internal Model Control. 4. PID controller design, *Industrial and Engineering Chemistry Process Design and Development*, Vol. 25, 1986, pp. 252-265.
- [178] Chien, I.-L., IMC-PID controller design - an extension, Proceedings of the *IFAC Adaptive Control of Chemical Processes Conference*, Copenhagen, Denmark, 1988, pp. 147-152.
- [179] Fruehauf, P.S., Chien, I.-L. and Lauritsen, M.D., Simplified IMC-PID tuning rules, Proceedings of the *ISA/93 Advances in Instrumentation and Control*, Chicago, Illinois, U.S.A., 1993, pp. 1745-1766.
- [180] Ogawa, S., PI controller tuning for robust performance, Proceedings of the *IEEE Conference on Control Applications*, 1995, pp. 101-106.
- [181] Lee, Y., Park, S., Lee, M. and Brosilow, C., PID controller tuning to obtain desired closed-loop responses for SI/SO systems, *AICHE Journal*, Vol. 44, 1998, pp. 106-115.
- [182] Morari, M. and Zafriou, E., *Robust process control*, Prentice-Hall Inc., 1989.
- [183] Horn, I.G., Arulandu, J.R., Gombas, C.J., VanAntwerp, J.G. and Braatz, R.D., Improved filter design in internal model control, *Industrial Engineering Chemistry Research*, Vol. 35, 1996, pp. 3437-3441.
- [184] Gong, X., Gao, J. and Zhou, C., Extension of IMC tuning to improve controller performance, Proceedings of the *IEEE International Conference on Systems, Man and Cybernetics*, 1996, pp. 1770-1775.
- [185] Thomasson, F.Y., Tuning guide for basic control loops, Proceedings of the *process control, electrical and information conference (TAAPI)*, 1997, pp. 137-148.
- [186] Alvarez-Ramirez, J., Morales, A. and Cervantes, I., Robust proportional-integral control, *Industrial Engineering Chemistry Research*, Vol. 37, 1998, pp. 4740-4747.
- [187] Rotstein, G.E. and Lewin, D.E., Simple PI and PID tuning for open-loop unstable systems, *Industrial Engineering Chemistry Research*, Vol. 30, 1991, pp. 1864-1869.
- [188] Jahanmiri, A. and Fallahi, H.R., New methods for process identification and design of feedback controller, *Transactions of the Institute of Chemical Engineers*, Vol. 75, Part A, 1997, pp. 519-522.
- [189] Huang, H.-P., Chien, I.-L., Lee, Y.-C. and Wang, G.-B., A simple method for tuning cascade control systems, *Chemical Engineering Communications*, Vol. 165, 1998, pp. 89-121.
- [190] Lee, Y., Park, S. and Lee, M., PID controller tuning to obtain desired closed loop responses for cascade control systems, *Industrial Engineering Chemistry Research*, Vol. 37, 1998, pp. 1859-1865.
- [191] Friman, M. and Waller, K.V., Autotuning of multiloop control systems, *Industrial Engineering Chemistry Research*, Vol. 33, 1994, pp. 1708-1717.
- [192] Semino, D. and Scali, C., Improved identification and autotuning of PI controllers for MIMO processes by relay techniques, *Journal of Process Control*, Vol. 8, 1998, pp. 219-227.
- [193] O'Dwyer, A., PI and PID controller tuning rules for time delay processes: a summary. Part 1: PI controller tuning rules, Submitted to the *Irish Signals and Systems Conference, 1999*, June.
- [194] O'Dwyer, A., PI and PID controller tuning rules for time delay processes: a summary. Part 2: PID controller tuning rules, Submitted to the *Irish Signals and Systems Conference, 1999*, June.
- [195] Harris, S.L. and Mellichamp, D.A., Controller tuning using optimisation to meet multiple closed loop criteria, *AICHE Journal*, Vol. 31, 1985, pp. 484-486.

- [196] Lee, J., Cho, W. and Edgar, T.F., An improved technique for PID controller tuning from closed loop tests, *AIChE Journal*, Vol. 36, 1990, pp. 1891-1895.
- [197] Nishikawa, Y., Sannomiya, N., Ohta, T. and Tanaka, H.: A method for auto-tuning of PID control parameters, *Automatica*, Vol. 20, 1984, pp. 321-332.
- [198] Patwardhan, A.A., Karim, M.N. and Shah, R., Controller tuning by a least-squares method, *AIChE Journal*, Vol. 33, 1987, pp. 1735-1737.
- [199] Gunn, J.A., Joseph, R.D. and Hurst, C.D., Robustness of optimal PID controllers, Proceedings of the *International Instrumentation Symposium*, Las Vegas, Nevada, U.S.A., 1987, pp. 469-476.
- [200] Zevros, C., Belanger, P.R. and Dumont, G.A., On PID controller tuning using orthonormal series identification, *Automatica*, Vol. 24, 1988, pp. 165-175.
- [201] Hassell, G.A. and Harper, R.E., Nonintrusive PID autotuning using dynamic modelling technology, *IEEE Conference Record of the Annual Pulp and Paper Industry Technical Conference*, 1994, pp. 1-6.
- [202] Schei, T.S., Automatic tuning of PID controllers based on transfer function estimation, *Automatica*, Vol. 30, 1994, pp. 1983-1989.
- [203] Di Ruscio, D., Adjustment of PID controller parameters, *Modeling, Identification and Control*, Vol. 13, 1992, pp. 189-197.
- [204] Abbas, A. and Sawyer, P.E., A multiobjective design algorithm: application to the design of SISO control systems, *Computers and Chemical Engineering*, Vol. 19, 1995, pp. 241-248.
- [205] Wang, L., Barnes, T.J.D. and Cluett, W.R., New frequency-domain design method for PID controllers, *IEE Proceedings - Control Theory and Applications*, Vol. 142, 1995, pp. 265-271.
- [206] Wang, F.-S., Yeh, C.-L. and Wu, Y.-C., PID controller tuning by an interactive multi-objective optimisation method, *Transactions of the Institute of Measurement and Control*, Vol. 18, 1996, 183-192.
- [207] Ham, T.W. and Kim, Y.H., Process identification using pulse response and proportional-integral-derivative controller tuning with combined guidelines, *Industrial Engineering Chemistry Research*, Vol. 37, 1998, pp. 482-488.
- [208] Hizal, N.A., Control system optimisation with the Ziegler-Nichols plant model, *Turkish Journal of Engineering and Environmental Sciences*, Vol. 21, 1997, pp. 83-87.
- [209] Astrom, K.J., Panagopoulos, H. and Hagglund, T., Design of PI controllers based on non-convex optimisation, *Automatica*, Vol. 34, 1998, pp. 585-601.
- [210] Ruano, A.E.B., Fleming, P.J. and Jones, D.I., Connectionist approach to PID autotuning, *IEE Proceedings, Part D*, Vol. 139, 1992, pp. 279-285.
- [211] Zhou, G. and Birdwell, J.D., Automation of PID autotuner design for complex systems, Proceedings of the *13th Triennial IFAC World Congress in Automatic Control*, San Francisco, CA., U.S.A., 1996, pp. 361-366.
- [212] Wu, C.-J. and Huang, C.-H., A hybrid method for parameter tuning of PID controllers, *Journal of the Franklin Institute*, Vol. 334B, 1997, pp. 547-562.
- [213] Radke, F. and Isermann, R., A parameter-adaptive PID-controller with stepwise parameter optimisation, Proceedings of the *IFAC 9th Triennial World Congress*, Budapest, Hungary, Vol. 4, 1984, pp. 1885-1890.
- [214] Cameron, F. and Seborg, D.E., A self-tuning controller with a PID structure, *International Journal of Control*, Vol. 38, 1983, pp. 401-417.
- [215] Ralston, P.A.S., Watson, K.R., Patwardhan, A.A. and Deshpande, P.B., A computer algorithm for optimised control, *Industrial and Engineering Chemistry Process Design and Development*, Vol. 24, 1985, pp. 1132-1136.
- [216] Bortolotto, G., Desages, A. and Romagnoli, J.A., Automatic tuning of PID controllers through response optimisation over a finite time horizon, *Chemical Engineering Communications*, Vol. 86, 1989, pp. 17-29.
- [217] Vega, P., Prada, C. and Aleixandre, V., Self-tuning predictive PID controller, *IEE Proceedings - Part D*, Vol. 138, 1991, pp. 303-311.
- [218] Yang, Y., Jia, C., Chen, J. and Lu, Y., Optimization method for PID controller design, *Computers in Industry*, Vol. 16, 1991, pp. 81-85.
- [219] Yamamoto, T., Omatu, S. and Kaneda, M., A design method for self-tuning PID controllers, Proceedings of the *American Control Conference*, Baltimore, Maryland, U.S.A., Vol. 3, 1994, pp. 3263-3267.
- [220] Miura, N., Imaeda, M., Hashimoto, K., Wood, R.K., Hattori, H. and Onishi, M., Auto-tuning PID controller based on generalised minimum variance control for a PVC reactor, *Journal of Chemical Engineering of Japan*, Vol. 31, 1998, pp. 626-632.
- [221] Kelly, J.D., Tuning digital PI controllers for minimal variance in manipulated input moves applied to imbalance systems with delay, *The Canadian Journal of Chemical Engineering*, Vol. 76, 1998, pp. 967-974.
- [222] Wang, F.-S. and Wu, T.-Y., Multiple loop PID controller tuning by the goal attainment trade-off method, *Transactions of the Institute of Measurement and Control*, Vol. 17, 1995, pp. 27-34.
- [223] Puleston, P.F. and Mantz, R.J., An anti-wind-up proportional integral structure for controlling time-delayed multiinput-multioutput processes, *Industrial and Engineering Chemistry Research*, Vol. 34, 1995, pp. 2993-3000.
- [224] Ham, T.W. and Kim, Y.H., Process identification and PID controller tuning in multivariable systems, *Journal of Chemical Engineering of Japan*, Vol. 31, No. 6, 1998, pp. 941-949.
- [225] Arzen, K.-E., *Realisation of expert system based feedback control*, Department of Automatic Control, Lund Institute of Technology, 1987.
- [226] Schuster, T., An adaptive PID-controller, *Periodica Polytechnica Series - Electrical Engineering*, Vol. 33, 1989, pp. 263-272.
- [227] Aguirre, L.A., PID tuning based on model matching, *Electronics Letters*, Vol. 28, 1992, pp. 2269-2271.
- [228] Abdelzahar, T.F.A. and Sheirah, M.A., Generalized PID tuning method, Proceedings of the *2nd IASTED Conference on Computer Applications in Industry*, Vol. 1, 1992, pp. 380-385.
- [229] Knoop, M., A novel approach to PID controller design for linear time delay systems, Proceedings of the *11th IASTED International Conference on Modelling, Identification and Control*, 1992, pp. 19-22.
- [230] Zhao, Z.-Y., Tomikuza, M. and Iskra, S., Fuzzy gain scheduling of PID controllers, *IEEE Transactions on Systems, Man and Cybernetics*, Vol. 23, 1993, pp. 1392-1398.
- [231] Persson, P. and Astrom, K.J., PID control revisited, Proceedings of the *IFAC 12th Triennial World Congress*, Sydney, Australia, 1993, pp. 451-454.
- [232] Hwang, S.-H. and Shiu, S.-J., A new autotuning method with specifications on dominant pole placement, *International Journal of Control*, Vol. 60, 1994, pp. 265-282.
- [233] Jin, B., An approach for auto-tuning of PID controllers, Proceedings of the *Asian Control Conference*, Tokyo, Japan, 1994, pp. 323-326.
- [234] Sung, S.W., Lee, I.-B. and Lee, J., Modified Proportional-Integral-Derivative (PID) controller and a new tuning method for the PID controller, *Industrial Engineering Chemistry Research*, Vol. 34, 1995, pp. 4127-4132.
- [235] Prokop, R. and Meszaros, A., Design of robust controllers for SISO time-delay systems, *Journal of Electrical Engineering*, Vol. 42, No. 11-12, 1996, pp. 287-294.
- [236] Daley, S. and Liu, G.P., Optimal PID tuning using direct search algorithms, Proceedings of the *Institute of Mechanical Engineers Seminar S576: Tuning-in to increase profit - developments in PID tuning*, London, U.K., 1998, Lecture 5.
- [237] Edgar, T.F., Heeb, R. and Hougen, J.O., Computer aided process control system design using interactive graphics, *Computers and Chemical Engineering*, Vol. 5, 1981, pp. 225-232.
- [238] Sanathanan, C.K. and Quinn, S.B., Design of set point regulators for processes involving time delay, *AIChE Journal*, Vol. 33, 1987, pp. 1873-1881.
- [239] Devanathan, R., An analysis of minimum integrated error solution with application to self-tuning controller, *Journal of Electrical and Electronics Engineering*, Australia, Vol. 11, No. 3, 1991, pp. 172-177.
- [240] Thomson, M., Cassidy, P.G. and Sandoz, D.J., Automatic tuning of PID controllers using a combined time- and frequency-domain method, *Transactions of the Institute of Measurement and Control*, Vol. 11, 1989, pp. 40-47.
- [241] Schei, T.S., A method for closed loop automatic tuning of PID controllers, *Automatica*, Vol. 28, 1992, pp. 587-591.
- [242] Kim, Y.H., PI controller tuning using modified relay feedback method, *Journal of Chemical Engineering of Japan*, Vol. 28, 1995, pp. 118-121.
- [243] Barnes, T.J.D., Wang, L. and Cluett, W.R., A frequency domain design method for PID controllers, Proceedings of the *American*

- Control Conference*, San Francisco, California, U.S.A., 1993, pp. 890-893.
- [244] Vrancic, D., Peng, Y. and Danz, C., A comparison between different PI controller tuning methods, *Report DP-7286*, University of Ljubljana, J. Stefan Institute, Ljubljana, Slovenia, 1995.
- [245] Vrancic, D. and Peng, Y., Amplitude and phase margin setting with on-line PI controller, Proceedings of the *CESA '96 IMACS multiconference symposium on control, optimisation and supervision*, Lille, France, Vol. 2, 1996, pp. 809-813.
- [246] Grassi, E. and Tsakalis, K., PID controller tuning by frequency loop shaping, Proceedings of the *35th Conference on Decision and Control*, Kobe, Japan, 1996, pp. 4776-4781.
- [247] Woodyatt, A. and Middleton, R., Auto-tuning PID controller design using frequency domain approximation, *Technical Report EE9629*, Department of Electrical and Computer Engineering, University of Newcastle, Callaghan NSW 2308, Australia, 1997.
- [248] Shafiei, Z. and Shenton, A.F., Tuning of PID-type controllers for stable and unstable systems with time delay, *Automatica*, Vol. 30, 1994, pp. 1609-1615.
- [249] Shafiei, Z. and Shenton, A.F., Frequency-domain design of PID controllers for stable and unstable systems with time delay, *Automatica*, Vol. 33, 1997, pp. 2223-2232.
- [250] Natarajan, K. and Gilbert, A.F., On direct PID controller tuning based on a finite number of frequency response data, *ISA Transactions*, Vol. 36, No. 2, 1997, pp. 139-149.
- [251] Natarajan, K. and Gilbert, A.F., System identification and PID controller tuning using band-pass filters, *The Canadian Journal of Chemical Engineering*, Vol. 75, 1997, pp. 765-776.
- [252] Leva, A., Automatic tuning of PID regulators in presence of model perturbations near the desired closed-loop cutoff, *European Journal of Control*, Vol. 3, 1997, pp. 150-161.
- [253] Wang, Q.-G., Hang, C.-C. and Bi, Q., A frequency domain controller design method, *Transactions of the Institute of Chemical Engineers*, Vol. 75, Part A, 1997, pp. 64-72.
- [254] Fung, H.-W., Wang, Q.-G. and Lee, T.-H., PI tuning in terms of gain and phase margins, *Automatica*, Vol. 34, 1998, pp. 1145-1149.
- [255] Tjokro, S. and Shah, S.L., Adaptive PID control, Proceedings of the *American Control Conference*, Vol. 3, 1985, pp. 1528-1534.
- [256] Vermeer, P.J., Morris, A.J. and Shah, S.L., Adaptive PID control - a pole placement algorithm with a single controller tuning parameter, Proceedings of the *IFAC Adaptive Control of Chemical Processes Conference*, Copenhagen, Denmark, 1988, pp. 159-164.
- [257] Pal, J., Nagar, S.K. and Sharma, J.D., Digital controller design for systems with transport lag, *International Journal of Systems Science*, Vol. 23, 1992, pp. 2385-2392.
- [258] Yang, J.-S., A parameter plane method for the PID control of a multirate, sampled-data chemical reactor system with a transportation lag, *Chemical Engineering Communications*, Vol. 122, 1993, pp. 227-244.
- [259] Yamamoto, T., Ishihara, H., Omatu, S. and Kitamori, T., Multivariable self tuning controller with I-PD structure, Proceedings of the *International Conference on Industrial Electronics, Control and Instrumentation (IECON '91)*, Kobe, Japan, Vol. 3, 1991, pp. 1812-1817.
- [260] Maffezzoni, C. and Rocco, P., Robust tuning of PID regulators based on step-response identification, *European Journal of Control*, Vol. 3, 1997, pp. 125-136.
- [261] Kawabe, T. and Katayama, T., A minimax design of robust I-PD controller for system with time delay, Proceedings of the *Asian Control Conference*, Tokyo, Japan, 1994, pp. 495-498.
- [262] Kawabe, T., Tagami, T. and Katayama, T., A genetic algorithm based minimax optimal design of robust I-PD controller, Proceedings of the *UKACC International Conference on Control*, 1996, pp. 436-441.
- [263] Hayes, M.J.M. and Holohan, A., High performance control of poorly modelled systems using PID feedback, Proceedings of the *Irish Digital Signal Processing and Control Conference*, Trinity College, Dublin, Ireland, 1996, pp. 365-371.
- [264] Da Silva, M.A., Gomide, F.A.C. and Amaral, W.C., A rule based procedure for selftuning PID controllers, Proceedings of the *27th Conference on Decision and Control*, Austin, Texas, U.S.A., 1988, pp. 1947-1951.
- [265] Seem, J.E., A new pattern recognition adaptive controller, Proceedings of the *13th IFAC Triennial World Congress*, San Francisco, CA., U.S.A., 1996, pp. 121-126.
- [266] Kraus, T.W. and Myron, T.J., Self-tuning PID controller uses pattern recognition approach, *Control Engineering*, June, 1984, pp. 106-111.
- [267] Litt, J., An expert system to perform on-line controller tuning, *IEEE Control Systems Magazine*, April, 1991, pp. 18-23.
- [268] Mahmoud, M.S., Abou-Elseoud, A.A. and Kotob, S., Development of expert control systems: a pattern classification and recognition approach, *Journal of Intelligent and Robotic Systems*, Vol. 5, 1992, pp. 129-146.
- [269] Hang, C.C. and Sin, K.K., Development of an intelligent self-tuning PID controller, Proceedings of the *ISA/92 International Conference and Exhibition. Advances in Instrumentation and Control*, Houston, Texas, Vol. 47(2), 1992, pp. 1101-1111.
- [270] Lee, T.H., Hang, C.C., Ho, W.K. and Yue, P.K., Implementation of a knowledge-based PID autotuner, *Automatica*, Vol. 29, 1993, pp. 1107-1113.
- [271] Ho, W.K., Lee, T.H. and Tay, E.B., Knowledge-based multivariable PID control, *Control Engineering Practice*, Vol. 6, 1998, pp. 855-864.
- [272] Acosta, G.G., Mayosky, M.A. and Catalfo, J.M., An expert PID controller uses refined Ziegler and Nichols rules and fuzzy logic ideas, *Journal of Applied Intelligence*, Vol. 4, 1994, pp. 53-66.
- [273] Tzafestas, S. and Papanikolopoulos, N.P., Incremental fuzzy expert PID control, *IEEE Transactions on Industrial Electronics*, Vol. 37, No. 5, 1990, pp. 365-371.
- [274] Ling, C. and Edgar, T.F., The tuning of fuzzy heuristic controllers, *Asia-Pacific Engineering Journal (Part A)*, Vol. 3, No. 1-2, 1993, pp. 83-104.
- [275] Xu, J.-X., Liu, C. and Hang, C.C., Tuning of fuzzy PI controllers based on gain/phase margin specifications and ITAE index, *ISA Transactions*, Vol. 35, 1996, pp. 79-91.
- [276] Xu, J.-X., Pok, Y.-M., Liu, C. and Hang, C.-C., Tuning and analysis of a fuzzy PI controller based on gain and phase margins, *IEEE Transactions on Systems, Man and Cybernetics - Part A: Systems and Humans*, Vol. 28, 1998, pp. 685-691.
- [277] Wang, P. and Kwok, D.P., Optimal design of PID process controllers based on genetic algorithms, *Control Engineering Practice*, Vol. 2, 1994, pp. 641-648.
- [278] Jones, A.H., Lin, Y.-C., De Moura Oliveira, P.B. and Kenway, S.B., Autotuning of dual-mode controllers using genetic algorithms, Proceedings of the *2nd International Conference on genetic algorithms in engineering systems: innovations and applications (GALESIA '97)*, University of Strathclyde, Glasgow, Scotland, 1997, pp. 516-521.
- [279] Vlachos, C., Evans, J.T. and Williams, D., PI controller tuning for multivariable processes using genetic algorithms, Proceedings of the *2nd International Conference on genetic algorithms in engineering systems: innovations and applications (GALESIA '97)*, University of Strathclyde, Glasgow, Scotland, 1997, pp. 43-49.